



# **STORM G A M E S** SAS Setup Instructions

Terminal #:	1	
Serial Port:	COM4	~
Serial Number:	123467891234	
Connection Status:	CONNECTED	

Revision: 1.0 Date: 4/1/25





#### Symbols Used in This Guide

Į

Indicates a **Note** or tip that the Operator should be aware of or may be helpful during the set up.

Indicates a **Warning** in which the Operator should pay close attention as an error may occur, damage to the machine, software or injury to the Operator may also occur.

#### Disclaimer

The information contained in this instruction manual is for information purposes only. Primero Games, LLC ("Primero") is not responsible for any errors or omissions, or for the results obtained, from the use of this information. All information in this instruction manual is presented "as is" with no guaranty of completeness, accuracy, or for the results obtained from its use. This instruction manual is not intended to be a safety guide. You must take all safety precautions that you believe are necessary. Your use of this information is at your own risk. This instruction manual is not a product warranty. PRIMERO MAKES NO EXPRESS OR IMPLIED WARRANTY AND DISCLAIMS ALL OTHER WARRANTIES WITH RESPECT TO THE INFORMATION CONTAINED HEREIN.

Version	Author / Contributors	Date	Changes / Comments
1.0	Shawn Lucci – Technical Writer Darren Breese – Director of Business Development Robert Curtis – Sr Back End Developer Chris Ward – Technical Services Supervisor	4.1.25	First Edition

## Main Menu

Once logged in, the Main Menu appears.

Тар	Terminal	Settinas to	access the	Printer and	Bill Acce	ptor settinas.

Main M	enu				
Terminal Audit	Eve	-	Terminal Sett	ings	
	Locati	on Name	Tick	et Interval	1 5
Bill History	Receip	Address	Mini	mum Ticket	1 - +
Gamepiay Stats	City		Spec	cial Win (\$)	50000
	State		Pin (	Code	1234
Terminal Settings	Zip		Alan	m	ON OFF
Settings	Suppo Volum Printer	e 30 -	Calit	brate Touchscreen	Select Manufacturer
	Printer	Port COM2	Bill	Acceptor Port	COM1 · INITIALIZE
	RAM	CLEAR			Set Date/Time





### Select the Printer Type

Printer Type	Pyramid	v	Tap to open the Select a Printer T	Printer Type Dropdov Type.	vn and
				Pyramid	
				None	
				Pyramid 🛑	

#### Select the Printer Port



Tap to open the Printer Port Dropdown and Select COM Port 2.

See Appendix A: Printers for supported printers and printer set up.





### Select the Bill Acceptor Type

Bill Acceptor Type ICT Tap the dropdown to select the Bill Acceptor.

ICT	, lov
None ID003	
PyramidApex	
ICT	
Mei	
MeiSerial	





#### Select the Bill Acceptor Port



Bill Validator set up.

**Note:** For Pyramid Apex Bill Acceptors, the Com Port must be set to COM3.

Bill Acceptor Type	PyramidApe	× ×
Bill Acceptor Port	COM3 ·	INITIALIZE

#### Tap Close to Save the Settings

<b>Fermin</b> a	al Settings		CLOSE 🗙
	Ticket Interval	1 5	
	Minimum Ticket	1 -	+
	Special Win (\$)	50000	
	Pin Code	1234	
	Alarm	ON OFF	





## **SAS Settings**

From the Main Menu Tap SAS Settings.

Main Menu	
Terminal Audit Event Log	Sas Configuration
Bill History Receipt History	Terminal #: 1
Gameplay Stats Game Recall	Serial Port: COM4 ~ Serial Number: 123467891234
Terminal Settings Game Settings	Connection Status: CONNECTED
SAS Settings Support Tools	The SAS Page allows the Operator to set up the Slot Accounting System.

#### Select the Terminal Number

Terminal #:

Tap the Text Box and use the Pop Up Keyboard to Enter a Value.

0

This is the number the SAS Host or Site Controller determines as the Terminal ID and is set to a value between 0 and 127.

Entering 0 will Disable the SAS system.



					4					8						PgUp	
																PgDn	
Caps									k				Ente			Pause	
Shift														Shif			Dock
		•														Help	Fade

COM1

### Select the Serial Port



Tap the Dropdown and Select COM4 as the Serial Port.







#### Set the Serial Number

Serial Number:

123467891234

Tap the Text Box to use the Pop Up Keyboard to Enter a Value.

The unique number generated by the SAS Host for TITO or AFT.



SAS Not Connected

### SAS Exceptions

The SAS Exceptions will only show if SAS is not connected and provides feedback to the Operator as to SAS connectivity.

erminai #:		l erminai #:		1
Serial Port:	COM4 ·	Serial Port:		COM1
Serial Number:	123467891234	Serial Num	ber:	1234567890
Connection Status:	CONNECTED	Connection	Status:	NOT CONNECTE
SasExceptions (	Data	SasExce	ptions D	ata
SasExceptions (	Data	SasExce Configuration Configuration	ptions ( D: DptionChange DptionChange	ata
SasExceptions (	Data	SasExce Configuration Configuration GameSelected	DeptionChange	ata
SasExceptions (	Data	SasExce Configuration Configuration GameSelected GameSelected	pptions ( Data DeptionChange ) DeptionChange ( ) 1	ata
SasExceptions (	Data	SasExce Configuration Configuration GameSelecter GameSelecter Configuration	pptionChange DptionChange 1 1 2ptionChange	ata
SasExceptions (	Data	SasExce Configuration Configuration GameSelected Configuration Configuration	pptions ( Da DationChange JoptionChange J JoptionChange DationChange	ata

#### SAS Connected





## Appendix A: Cabinet Set Up

#### For Storm on EFCO 8657

#### **Bill Acceptors**

**Innovative NV200 on Serial** - Connect to Any Valid COM Port. ID003\_V2 Select COM4 from the Bill Acceptor Port dropdown and Select

**JCM UBA on Serial** - Connect to Any Valid COM Port. ID003\_V2 Select COM4 from the Bill Acceptor Port dropdown and

**Pyramid Apex 7600 USA on Serial** - Connected to COM3. Select PyramidApex from the Bill Acceptor dropdown and Select COM3 from the Bill Acceptor Port dropdown. Firmware: USA 1.16 SS5.

#### Cables

180038 Bill Acceptor - UBA Data Cable (Rev. B) 180081 Bill Acceptor - NV200 Cable Harness 530310 Cable - Pyramid Apex 7600, TTL RS232 [8 ft], ["MEI Bypass"]

#### Hard Drive Requirements

Transcend 256GB TS256GMTE712P-PRI